

# Aura Par 1915Z

## User Manual



**Guangzhou Mitek Light Co.,LTD**

Email: [info@miteklight.com](mailto:info@miteklight.com)

Website: [www.miteklight.com](http://www.miteklight.com)

Add: No. 21 Dongfeng Avenue, Automobile Industry Base, Huadu District, Guangzhou

## TECHNICAL PARAMETERS

### Light source

Rated voltage: AC100-240V, 50/60HZ.

Rated power: 150W

LED: 19\*15W 4-IN-1 RGBW LEDs

### Controls

Control mode: self-propelled, voice control, DMX512, master-slave Color: independent  
4-color effects, unlimited color mixing combinations

### Effect

10°-50°Smooth and quiet linear zoom

Shapes built-in WITH AURA EYE CANDY

### Weight&Dimension

Size:31\*23.5\*21.5cm

N.W:3.2kg

Inner box size: 28.5\*28\*28.5cm

Outer box size: 59\*58\*31.5cm

Box size: 4PCS

G.W: 20KG

## SIZE DRAWING



## Display panel operation



After boot, press MENU to switch menu, press UP (up) DOWN (down) to select the value size, and then press ENTER(OK) to save, no key operation after 30 seconds automatic screen saver, press any key to activate.

A001	A001-512	DMX Mode
CH17	CH09/CH17	Channel mode
FF50	FF01-99	Color Jump
CC50	CC01-99	Color Gradient
EE50	EE01-99	Color Pulse
Auto		Auto mode
SoU1	SoU1-2	Voice-activated mode, two effects
R255	R000-255	Red manual dimming
G255	G000-255	Green manual dimmer
b255	b000-255	Blue manual dimming
W255	W000-255	White manual dimming
S000	S000-255	Stroboscopic mode 1-20Hz
F000	F000-255	Spot Angle zoom
Two: channel table		

## Channel table

9 Channels	17 channels	Channel values	Function description
CH1	CH1	0-255	Total dimming 0-100% linear dimming
CH2	CH2	0-255	Strobe from slow to fast 1-20Hz
CH3	CH3	0-255	The spot Angle scales linearly, from small to large
CH4	CH4	0-255	Red 1 0-100% linear dimming
CH5	CH5	0-255	Green 1 0-100% linear dimming
CH6	CH6	0-255	Blue 10 0-100% linear dimming
CH7	CH7	0-255	White 1 0-100% linear dimming
CH4	CH8	0-255	Red 1 0-100% linear dimming
CH5	CH9	0-255	Green 1 0-100% linear dimming
CH6	CH10	0-255	Blue 10 0-100% linear dimming
CH7	CH11	0-255	White 1 0-100% linear dimming
CH4	CH12	0-255	Red 10 0-100% linear dimming
CH5	CH13	0-255	Green 1 0-100% linear dimming
CH6	CH14	0-255	Blue 10 0-100% linear dimming
CH7	CH15	0-255	White 1 0-100% linear dimming
CH8	CH16	0-15	No Features
		16-135	15 color options
		136-143	Color Jump
		144-151	Color gradient
		152-159	Color pulse

		160-239	10 self-walking effects
		240-247	Voice-activated mode 1
		248-255	Voice-activated Mode 2
CH9	CH17	0-255	Speed from slow to fast

**Note:** Plug in the signal cable, the lamp automatically recognizes and jumps to DMX mode, and the first digit tube flashes.

Three: master and slave setting.

2 or more of the same lamps are connected with 3-core signal cables, and any host is set as a demonstration program

The other machine automatically recognizes the signal

## REMARK

The product has perfect performance and integrity packing.

All users should be strictly comply with the warning and operating instructions as stated.

Or we aren't in charge of any result by misusing.

Any damage resulting by misuse is not within the Company's warranty.

Any fault or problem caused by neglecting the manual is also not in the charge of dealers.

Errors and omissions for every information given in this manual excepted.

All information is subject to change without prior notice.