

Blinder 2

User Manual



Guangzhou Mitek Light Co.,LTD

Email: info@miteklight.com

Website: www.miteklight.com

Add: No. 21 Dongfeng Avenue, Automobile Industry Base, Huadu District, Guangzhou

TECHNICAL PARAMETERS

Light source

Voltage: AC110-220V 50/60HZ

Power supply: 200W

Light source: 100W*2PCS

Color: W,Y

Controls

Channel:8/4CH

Operation: DMX512, Auto, Sound, Master-slave

Weight&Dimension

Package: 4PCS/CARTON

Thank you so much to choose this product; it is adopting the most advanced lamps, which is called LED lamps. It conquers a lot of disadvantages such as power wasting, short using life, high temperature, etc. It has advantages of power saving, long life (it can reach 60,000.00 hours in general circs), high brightness, fresh colors...It is the best stage illuminating and various effect decorative products.

Security:

1. Make sure the user voltage cannot higher or lower than the regulate value of the user manual.
2. Please take more attention while installing the fixtures. Avoid touching exposed AC cord, or will cause deadly accident.
3. When installing the fixtures, make sure the fixtures are not exposed in extremely hot, humid or dusty environment. Make sure the distance between the fixture and the lighted object is not less than 0.5 meter. Make sure there is no combustible or explosive object around 0.5 meters.

DMX DISPLAY

NO.	Show	Function	Instruction
1	d001	DMX Address (001~512)	DMX-512 address set, 4 Channels mode
2	A001	DMX Address (001~512)	DMX-512 address set, 8 Channels mode
3	r255	Y (000~255)	UP、DOWN Change brightness
4	G255	W (000~255)	UP、DOWN Change brightness
5	b255	Y (000~255)	UP、DOWN Change brightness
6	u255	W (000~255)	UP、DOWN Change brightness
7	FH99	trobe flash (01~99)	UP、DOWN Change the speed
8	CL01	Different Colors Output (01~08)	UP、DOWN Change brightness
9	CC99	Colors Jump Change (01~99)	UP、DOWN Change the speed
10	DE99	Colors Gradate (01~99)	UP、DOWN Change the speed
11	CP99	Colors Pulse	UP、DOWN Change the speed

		Change (01~99)	
12	SU01	Colors sound-Active (01~09)	UP、DOWN Change the effects

DMX512Control : 8 Channel Model

Channel	Function	Description
Channel 1	Dimmer all	Dimmer all from darkness to brightness
Channel 2	Dimmer Y	Dimmer Y from darkness to brightness
Channel 3	Dimmer W	Dimmer W from darkness to brightness
Channel 4	Dimmer Y	Dimmer Y from darkness to brightness
Channel 5	Dimmer W	Dimmer W from darkness to brightness
Channel 6	Strobe all	Strobe all, from slow to fast
Channel 7	Function speed	Function speed, from slow to fast
Channel 8	Function selection	0-15: DMX dimmer 51-100: Regular color export 101-150: Jump change running 151-200: Gradual change running 201-250: Pulse change running 251-255: Sound control

DMX512Control: 4Channel Model

No	function	Description
Channel 1	Dimmer Y	Dimmer Y from darkness to brightness
Channel 2	Dimmer W	Dimmer W from darkness to brightness
Channel 3	Dimmer Y	Dimmer Y from darkness to brightness
Channel 4	Dimmer W	Dimmer W from darkness to brightness

REMARK

The product has perfect performance and integrity packing.

All users should be strictly comply with the warning and operating instructions as stated.

Or we aren't in charge of any result by misusing.

Any damage resulting by misuse is not within the Company's warranty.

Any fault or problem caused by neglecting the manual is also not in the charge of dealers.

Errors and omissions for every information given in this manual excepted.

All information is subject to change without prior notice.